

MINIKOM LAUNCH AMPLIFIER

WITH GAIN LEVEL REGULATION




REF.	ART. NR.	DESCRIPTION	EAN 13
531710	NV3038	AMP. MINIKOM RET+MATV+IF "F" G(-5)/35/33..38	8424450188385



This is a line launch amplifier, so it has one input and one output. It is suitable for SMATV/CATV systems, it covers the return path bands, VHF/UHF and IF (SAT).

- IF and MATV attenuation and equalization control.
- LED's indicating output signal.
- Easy installation.
- High shielding chassis, made of Zamak.
- Low consumption.



REF.	ART. NR.	 mm	 g	 U./Pack.
531710	NV3038	182 x 117 x 57	710	1/box



		RETURN PATH		FORWARD PATH	
		RET	TERR	FI (SAT)	
Frequency range	MHz	5...30	47...862	950...2150	
Gain	dB	-5	35	33-38	
Return loss	dB	12	10	10	
Output level	EN50083-3	IMD3 (2ch-25dB)	-	127	123
		IMD2 (2ch-35dB)	-	-	119
	DIN 45004B		-	120	-
	42 CH CENELEC	CTB, CSO (-60dB)	-	98	-
Gain regulation range	dB	-	0...20	0...20	
Equalization range	dB	-	0...20	0...15	
Noise figure	dB	-	8	-	
Input power	V~	196-253			
Max. consumption	W	9			
Temperature conditions	°C	-5...+45			

